



Mixer Amplifier (Phone Jack MIC Input)

T-35M/T-60M



Feature:

- * 3 MIC inputs, 2 AUX inputs.
- * 3 MIC volume control, 2 AUX volume control.
- * With priority, MIC1 input is prior to other audio inputs.
- * Separate treble and bass adjustment knob.
- * One MIC2 / AUX1 selector switch, one MIC3 / AUX2 selector switch.
- * Two types of power output: 4 ohm, 8 ohm and 70V, 100V output.
- * Single-channel rated power 35W / 60W output.

Specifications:

Model	T-35M	T-60M
Rated Power Output	35W	60W
Speaker Outputs	70V, 100V & 4-8Ω	
Input Sensitivity & Impedance	MIC 1, 2, 3: 5mV/600Ω MIC2: 775mV/10KΩ AUX2: 350mV/10KΩ	
Output Sensitivity & Impedance	MIX OUT: 1V/470Ω	
Tone	Bass: ±10dB at 100Hz Treble: ±10dB at 10KHz	
Frequency Response	50Hz-16KHz (+1dB, -3dB)	
S/N Ratio	MIC 1, 2, 3: 66dB, AUX 1, 2: 80dB	
THD	Less than 0.5% at 1KHz, 1/3 rated power	
Crosstalk	≤50dB	
Cooling	Fan automatically start up when temp reaches 55°C	
Protection	High temp, overload & short-circuit	
Power Supply	~110V-230V 50/60Hz	
Power Consumption	60W	100W
Weight	3Kg	3.5Kg
Dimensions	484 x 335 x 88mm	
Finish	Panel: aluminum plate, black Case: SPCC Panel	