



## Feature

\* 2-in 8-out antenna signal splitter equipment.

- \* Simplify the antenna assembly process and improve the receiving distance and performance.
- \* The two antenna signals are received at the antenna input end of the splitter.
- \* The two signals are output to the antenna input end of the next splitter for cascading.

## Specification

Model	T-526A
Frequency range	450MHz-950MHz
Total gain	0dB, ±2dB
Input/Output impedance	50Ω
Antenna power supply	+12V DC/ 0.1A, center point is positive
DC output	12V DC/3A (MAX)*4 groups, center point is positive
Power supply	100-240V AC, 50/60Hz, 12V DC/3A
Connector port	BNC
Product size	428*177*45.2mm
Package size	520*475*90mm
Netweight	2.9kg
Gross weight	3.36kg