



## **Description**

T-7701 is a popular model installed in low voltage room or sub control center, linking to 2 power amplifiers. It is ideal choice to broadcast in hall, corridor, outdoor areas etc.

## **Features**

- $^{st}$  It is a 19 inck mount IP/TCP network audio adapter, with black alumina panel, strong handle, professional mechanical assembly process, high-end appearance.

  \* Built-in 3.4 inch LCD screen to clearly display most of lattice pattern and working state.
- \* Embedded PC technology, built-in DSP Audio processing technology and high speed industrial chip to ensure start time less than 1 second.
- \* Built-in single network hardware audio decoding module, support TCP/IP, UDP, IGMP (Multicast)
- protocol, transmit 16-bit stereo audio signal of CD quality through network.

  \* 1 AUX and 1 Mic input. Support independent bass and treble adjustment and support offline local paging function.
- \* 1 EMC input, for emergency alarm voice signal connection, with the highest priority.

  \* 2 AUX output , to extend external power amplifier, RCA interface, easy connection.
- \* 2-channel 3 wired relay output for volume control, no need extra 24V DCpower supply, compatible with 4 wired fire alarm relay at the same time, which requires 24V strong power supply.

  \* Built-in intelligent power management, automatic power off if no signal, output signal
- automatically open when there is power supply, support IP software preset programming to switch on the power.
- \* Built-in 3 priority settings:
- 1) EMC is with the highest priority.
- 2) Network alarm is prior to MIC, AUX and BGM signal.
- 3) MIC is prior to AUX and BGM signal.
- 4) AUX and BGM is same without priority.
- \* Support preset mute adjustment, background music, LED indicators, including the level, protection, standby indicator. Support authorized operation management, with unified configuration and management for user password by the server.
- \* Support DHCP, compatible routers, switches, Bridges, Modem, Internet, 2G, 3G, 4G, multicast, unicast
- \* The digital products is more convenient for extension, no limit by the geographical position, no need increase management equipment for control center, sharing network to save cabling, or simple installation

## **Specifications**

T-7701
RJ45
100Mbps
TCP/IP,UDP,IGMP(Multicast)
MP3
16 bit CD quality
8K~48KHz
775mV (Unbalance)
350mV (Unbalance)
5mV (Unbalance)
1000mV 2 road lotus output interface
470Ω
$\pm 10 dB$
$\pm$ 1 OdB
80Hz~16KHz
10W
≤ 0.3%
>65dB
5℃~40℃
20%~80% Relative humidity, without condensation
~220-240V 50/60Hz
484×303×88mm
5.2Kg

## Rear Panel

